

## ASUS PRIME X670-P-CSM AMD X670 Socket AM5 ATX

**Brand :** ASUS

**Product code:** 90MB1BU0-M0EAYC

**Product name :** PRIME X670-P-CSM

PRIME X670-P-CSM Gaming Mainboard Socket AMD AM5 (Ryzen 7000, ATX, PCIe 5.0, 3x M.2, DDR5-Speicher, USB 3.2 Gen 2x2 Typ-C, Aura Sync RGB-Beleuchtung)

ASUS PRIME X670-P-CSM. Processor manufacturer: AMD, Processor socket: Socket AM5, Compatible processor series: AMD Ryzen 7 7th Gen, AMD Ryzen 9 7th Gen. Supported memory types: DDR5-SDRAM, Maximum internal memory: 128 GB, Memory slots type: DIMM. Supported storage drive interfaces: M.2, SATA III, Supported storage drive types: HDD & SSD, RAID levels: 0, 1, 10. Maximum resolution: 7680 x 4320 pixels. Ethernet interface type: 2.5 Gigabit Ethernet, Fast Ethernet, Gigabit Ethernet



Processor		Rear panel I/O ports	
Processor manufacturer *	AMD	USB 3.2 Gen 2 (3.1 Gen 2) Type-A ports quantity *	3
Processor socket *	Socket AM5	USB 3.2 Gen 2x2 Type-C ports quantity	1
Compatible processor series *	AMD Ryzen 7 7th Gen, AMD Ryzen 9 7th Gen	Ethernet LAN (RJ-45) ports *	1
Supported processor sockets	Socket AM5	PS/2 ports quantity	1
Memory		HDMI ports quantity *	1
Supported memory types *	DDR5-SDRAM	HDMI version	2.1
Number of memory slots *	4	DisplayPorts quantity	1
Memory slots type	DIMM	DisplayPort version	1.4
Memory channels	Dual-channel	Network	
ECC	✓	Ethernet LAN	✓
Non-ECC	✓	Ethernet interface type	2.5 Gigabit Ethernet, Fast Ethernet, Gigabit Ethernet
Supported memory clock speeds	4800,5100,5200,5400,5600,5800,6000,6200,6400 MHz	Wi-Fi *	✗
Supported memory clock speed (max)	6400 MHz	Features	
Maximum internal memory *	128 GB	Motherboard chipset *	AMD X670
Unbuffered memory	✓	Audio output channels *	7.1 channels
Storage controllers		Component for *	PC
Supported storage drive types	HDD & SSD	Motherboard form factor *	ATX
Supported storage drive interfaces *	M.2, SATA III	Motherboard chipset family *	AMD
RAID support	✓	Windows operating systems supported	Windows 10 x64, Windows 11 x64
RAID levels	0, 1, 10	Expansion slots	
Graphics		PCI Express x1 (Gen 3.x) slots	1
Parallel processing technology support *	Not supported	PCI Express x16 (Gen 4.x) slots	3
Maximum resolution	7680 x 4320 pixels	Number of M.2 (M) slots	3
Internal I/O		BIOS	
USB 2.0 connectors *	2	BIOS type *	UEFI AMI
USB 3.2 Gen 1 (3.1 Gen 1) connectors *	3	BIOS memory size	256 Mbit
Number of SATA III connectors *	6		
S/PDIF out connector	✓		
Front panel audio connector	✓		

Internal I/O		Packaging data	
Front panel connector	✓	Package width	338 mm
ATX Power connector (24-pin)	✓	Package depth	273 mm
CPU fan connector	✓	Package height	68 mm
Number of chassis fan connectors	3	Package weight	1.82 kg
Peripheral (Molex) power connectors (4-pin)	1	<b>Weight &amp; dimensions</b>	
EPS power connector (8-pin)	✓	Width	305 mm
Number of COM connectors	1	Depth	244 mm
TPM connector	✓	<b>Packaging content</b>	
Thunderbolt headers	1	Cables included	SATA
12V power connector	✓	User guide	✓
RGB LED pin header	✓	<b>Other features</b>	
<b>Rear panel I/O ports</b>		ASUS 5X PROTECTION III - DIGI+ VRM (- Digital power design with DrMOS) - ESD Guards - LANGuard - Overvoltage Protection - Safeslot Core+ - Stainless-Steel Back I/O	
USB 2.0 ports quantity *	2	ASUS Q-Design - M.2 Q-Latch - Q-DIMM - Q-LED Core - Q-Slot ASUS Thermal Solution - M.2 heatsink - VRM heatsink design ASUS EZ DIY - BIOS FlashBack™ button - BIOS FlashBack™ LED - ProCool Aura Sync - Aura RGB headers - Addressable Gen 2 headers	
USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	4	Special features	
		Packaging content	Cables 2 x SATA 6Gb/s cables Miscellaneous 1 x I/O Shield 1 x Rubber Package for M.2 2 x Screw Packages for M.2 SSD Documentation 1 x User guide



4711081892847

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.